

DIMMER TEST

	Moon Slim 255	Moon Slim 320	Moon Slim 380	Moon Pro 255	Moon Pro 320	Moon Pro 420
SWEDEN						
SCHNEIDER 200LED 1350113 Rotary	1-10pcs 15-100%	1-10pcs 15-100%	1-10pcs 5-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 10-100%
SCHNEIDER 315RC 1370602 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 10-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
SCHNEIDER CCT99100 1360217 Pressure	1-10pcs 15-100%	1-10pcs 5-100%	1-10pcs 15-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 10-100%
SCHNEIDER LED Exx RC 370 1360752 Rotary	-	-	1-10pcs 10-100%	-	-	-
SCHNEIDER Exxact Wiser 1360432 Pressure 	1-10pcs 5-100%	1-10pcs 5-100%	1-8pcs 10-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
SCHNEIDER Exxact LED BT 1360395 Pressure 	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 10-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELKO 400GLI 1363071 Rotary	-	-	-	-	-	-
ELKO 315GLE 1363115 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELKO 314 GLED RS 1363149 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELKO 100W LED 1363241 Pressure	1-10pcs 15-100%	1-10pcs 10-100%	1-4pcs 15-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 10-100%
ELKO 150W LED 1363242 Pressure	1-10pcs 5-100%	1-10pcs 5-100%	1-6pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELTAKO 1377065 Pressure	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
VADSBO VD300 LED 1360391 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
VADSBO LD220 1377440 Pressure	1-10pcs 5-100%	1-10pcs 5-100%	1-8pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
VADSBO LF220WCM 1330242 Pressure 	1-10pcs 5-100%	1-10pcs 5-100%	1-8pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ABB LED 1360366 Rotary	-	-	-	1-5pcs 5-100%	-	-
Plejd DIM-01 1377701 Pressure 	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
Plejd DIM-02 1377703 Pressure 	1-10pcs 5-100%	1-10pcs 5-100%	1-4pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
Nexa NXT 200VA 1710817 Pressure	1-10pcs 5-100%	1-10pcs 5-100%	1-8pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
Round DALI/Push 200W 1360591 Pressure	1-10pcs 5-100%	1-10pcs 5-100%	1-8pcs 5-100%	-	-	-
NORWAY						
ELKO 315GLE 1471444 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELKO 400GLI 1471450 Rotary	-	-	-	-	-	-
UNILED SE45004 1404470 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	-
ELKO 420GLE 1471479 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELKO 316LED 1471474 Rotary	-	-	-	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ELTAKO EUD61NPN-230V 1438881 Pressure	-	1-10pcs 5-100%	1-8pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	-
FINLAND						
SCHNEIDER 315RC 2622161 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
SCHNEIDER 630RC 2622171 Rotary	-	-	-	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
ABB LED 2619376 Rotary	-	1-10pcs 5-100%	1-10pcs 10-100%	1-5pcs 10-100%	1-5pcs 5-100%	-
SCHNEIDER SBD200 LED 2622225 Rotary	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 10-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
SCHNEIDER SD400 2622351 Rotary	-	-	1-10pcs 5-100%	-	-	-
DENMARK						
LK FUGA MEK-S LED 506D6218 I Slide 5703302153829	1-10pcs 15-100%	1-10pcs 15-100%	1-5pcs 15-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 10-100%
LK FUGA Touch LED 506D6126 I Touch 5703302160742	1-10pcs 10-100%	1-10pcs 5-100%	1-7pcs 10-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 15-100%
LK FUGA MEK-S RC 506D5116 I Slide 5703302109871	1-10pcs 5-100%	1-10pcs 5-100%	1-10pcs 10-100%	1-5pcs 5-100%	1-5pcs 5-100%	1-5pcs 5-100%
LK FUGA MEK-D x 506D6109 I Rotary 5703302109918	1-10pcs 10-100%	1-10pcs 10-100%	1-10pcs 15-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 5-100%
LK FUGA IHC Wireless 505D6102 5703302127332	1-10pcs 10-100%	1-10pcs 10-100%	1-10pcs 15-100%	1-5pcs 10-100%	1-5pcs 10-100%	1-5pcs 5-100%

! Selected dimmers are a few examples of what the market has to offer. Always follow the dimmer manufacturer's recommendations with any loads and settings for the best effect. The result is an outcome of our tests and may vary depending on the installation.